

MP1000PIII 350W 3 Mic & 2 AUX Mixing Amplifier



Features

- 70V, 100V & 4-16 Ω , rated power 350W
- 3 microphone inputs, Mic 1 with priority and muting function
- 2 aux line input & 1 line output for additional mixer or amplifier link
- Individual volume control for each microphone and line input
- Bass and treble control.

Description

MP1000PIII economy mixer amplifier is rated at 350W. It has 3 microphone inputs and 2 aux inputs, and Mic 1 is provided with priority and muting function. Bass and treble controls and master volume control are provided. Complete protection includes short circuit and thermal protection, current limiter and overloading.

Specification

| | |
|-------------------------------------|---|
| Model | MP1000PIII |
| Rated output | 350W |
| Speaker output | 70V, 100V & 4-16 Ω , |
| Input sensitivity | Mic2,3 : 600 Ω , \leq 3mV, unbalanced ;AUX1,2,MIC1 : 10k Ω , \leq 300mV |
| Frequency response | 50Hz -16kHz (\pm 3dB) |
| Distortion | < 1% at 1kHz , 1/3rated output voltage |
| The ratio of signal to noise | Mic1,2 and 3 : >75dB ;AUX1 and 2 : > 80dB |
| Protection | AC fuse; DC voltage; overload; short-circuit. |
| Power requirements | AC 220V-240V/50Hz-60Hz |
| Power consumption | 650W |
| Outer Packing Size (mm) | (L×W×H)520×430×195 |
| Unit Size (mm) | (L×W×H)420×338×88 |
| Net weight | 13.4kg |

PRECAUTION OF INSTALLATION

1. Do not block ventilation holes.
2. The amplifier should not be placed in any of the areas:
 - 1) with poor ventilation;
 - 2) exposed to direct sunlight;
 - 3) with high ambient temperature or adjacent to heat-generating equipment;
 - 4) with high humidity or heavy dust;
 - 5) susceptible to vibration.
3. Make sure the power outlet conforms to the plug of the unit.
4. Do not use this unit if the electrical power cord is frayed or broken.

Always operate the unit with the AC ground wire connected to the electrical system's ground.

5. If an alarm rings after the power has been on and the signal has been fed, there must be an of output short-circuit trouble. In a such case,
please turn the power off. Do not turn on the power again, until the trouble shall be resolved.

PACKING LIST

| Sequence number | Category | Amount |
|-----------------|----------------------------------|--------|
| 1 | SY542 connectors (AV Audio line) | 1 |
| 2 | Output Insurance Box | 1 |
| 3 | Mains Line | 1 |
| 4 | Warranty Card | 1 |
| 5 | Certificate | 1 |
| 6 | User's Manual | 1 |

