

PC1008RII AM/FM Tuner



Features

- Microcomputer control, digital tuning system.
- Touch button control, VFD display operation status.
- ➤ 40 radio stations for storage in AM band and FM band respectively, and the stored radio stations can be recalled at any time.
- With auto radio stations searching and storage.
- > With audio signal level indicator.
- With permanent power-off memory.
- Support PC remote control.



Specification

| | FM | 87.0-108.0MHz |
|-------------------------|---------------------|---------------|
| Receiving Range | | |
| | AM | 522-1620kHz |
| Sensitivity | FM | 4dBμ |
| | AM | 35dBμ |
| SNR | FM | >60dB |
| | AM | >70dB |
| Tuning Frequency Step | FM | 1kHz |
| | AM | 1kHz |
| IF Frequency | FM | 10.7 MHz |
| | AM | 450 kHz |
| Maximum Output Level | 1.8dBV | |
| Protection | AC fuse | |
| Power | AC220V/50Hz | |
| Package Dimensions (mm) | (L×W×H) 555×455×185 | |
| Machine Dimensions (mm) | (L×W×H) 484×320×88 | |
| Gross Weight | 7.5kg | |
| Net Weight | 5.7kg | |