



## Mini40II Bluetooth Power Amplifier



## **Features**

- •Built-in 2x20W stereo Class D amplifier
- •8 ohms speaker output
- Support wireless Bluetooth 2.1+EDR
- •1 AUX input and 1 AUX output for power extension
- With remote controller for convenient use
- Aluminum-alloy casing, small size and portable
- •Power supply: AC110V-230V/50Hz/60Hz
- With hooks at the bottom for wall mount installation

## **Descriptions**

This is a wallmount bluetooth amplifier with small size, it has 1 Aux input and 1 Aux output for power extension, it support  $8\Omega$  speaker output, the dimension is very small with 130x123x42mm, it have very clearly sound experience. The device can meet the requirements of the users and can be widely applied in classroom, stores, Coffee shop and other small place.





## **Specifications**

Item	Mini40II
Rated Power	2×20W/8Ω
Freq. Resp.	20Hz-20KHz
Distortion	< 0.3%
SNR	> 82dB
Matched Impedance	$8\Omega$
LINE IN Sensitivity	0dB(1V)
LINE IN Impedance	> 10KΩ
BT Transmission	10m
BT Standard	BT2.1+EDR
Power Supply	AC110V-230V/50Hz/60Hz
Net Weight	0.33KG
Gross Weight	0.35KG
Product Dimension	130mm ×123mm×42mm